


Q.850 Cause Codes - Reference

 This page lists the **Q.850 Cause Codes** and their associated definition configurable on the SBC 1000/2000 (UX) system via the [SIP to Q.850 Cause Code Mapping](#) and [Q.850 Cause Code to SIP Mapping](#) resources.

| Code | Definition |
|------|---|
| 1 | Unallocated Number |
| 2 | No Route to Transit Network |
| 3 | No Route to Destination |
| 4 | Send Special Information tone |
| 5 | Misdialed Trunk Prefix |
| 6 | Channel Unacceptable |
| 7 | Call Awarded in Established Channel |
| 8 | Preemption |
| 9 | Preemption - Circuit Reserved for Reuse |
| 16 | Normal Call Clearing |
| 17 | User Busy |
| 18 | No User Responding |
| 19 | No Answer from User (user alerted) |
| 20 | Subscriber Absent |
| 21 | Call Rejected |
| 22 | Number Changed |
| 23 | Redirection to New Destination |
| 25 | Exchange Routing Error |
| 26 | Non-selected User Clearing |
| 27 | Destination Out of Order |
| 28 | Invalid Number Format (addr incomplete) |
| 29 | Facility Rejected |
| 30 | Response to STATUS ENQUIRY |
| 31 | Normal, Unspecified |
| 34 | No Circuit/Channel Available |
| 38 | Network Out of Order |
| 39 | Permanent Frame Mode Connection OoS |

| | |
|----|--|
| 40 | Permanent Frame Mode Connection Oper |
| 41 | Temporary Failure |
| 42 | Switching Equipment Congestion |
| 43 | Access Information Discarded |
| 44 | Requested Circuit/Channel N/A |
| 46 | Precedence Call Blocked |
| 47 | Resource Unavailable, Unspecified |
| 49 | Quality of Service Not Available |
| 50 | Requested Facility Not Subscribed |
| 53 | Outgoing Calls Barred Within CUG |
| 55 | Incoming Calls Barred Within CUG |
| 57 | Bearer Capability Not Authorized |
| 58 | Bearer Capability Not Available |
| 62 | Inconsistency in Outgoing IE |
| 63 | Service or Option N/A, unspecified |
| 65 | Bearer Capability Not Implemented |
| 66 | Channel Type Not Implemented |
| 69 | Requested Facility Not Implemented |
| 70 | Only Restricted Digital Bearer Cap supported |
| 79 | Service or Option Not Implemented, Unspecified |
| 81 | Invalid Call Reference Value |
| 82 | Identified Channel Does Not Exist |
| 83 | Call Exists, but Call Identity Does Not |
| 84 | Call Identity in User |
| 85 | No Call Suspended |
| 86 | Call with Requested Call Identity has Cleared |
| 87 | User Not Member of CUG |
| 88 | Incompatible Destination |
| 90 | Non-existent CUG |
| 91 | Invalid Transit Network Selection |
| 95 | Invalid Message, Unspecified |
| 96 | Mandatory Information Element is Missing |

| | |
|------------|--|
| 97 | Message Type Non-existent / Not Implemented |
| 98 | Message Incompatible With Call State or Message Type |
| 99 | IE/Parameter Non-existent or Not Implemented |
| 100 | Invalid Information Element Contents |
| 101 | Message Not Compatible With Call State |
| 102 | Recovery on Timer Expiry |
| 103 | Parameter Non-existent / Not Implemented, Passed On |
| 110 | Message With Unrecognized Parameter, Discarded |
| 111 | Protocol Error, Unspecified |
| 127 | Interworking, Unspecified |