

POST fxslocallooptype

REST API Method: **POST /rest/fxslocallooptype**

Modifies FXS Local Loop Type per line card in the SBC Edge. Long local loop will enable FXS ports to operate normally even if the phone is placed up to 3000 meters away from the SBC Edge.

- ✔ For SBC 2000, each FXS line card can be set to support long local loop independent of the other. For SBC 1000, only FXS line cards in the lower slots can be configured for long local loop and any FXS line card in the corresponding upper slot will get disabled.

URL:

https://192.168.0.111/rest/fxslocallooptype


HTTP Method




POST

Requires Authentication:

true

Parameters

Parameter Name	Required	Service Affecting	Data Type	Default Value	Possible Values	Description
CardOneLocalLoopType	Yes	Yes	isdn_tip:LOCAL_LOOP_LENGTH			Identifies the FXS line card in the first slot of the SBC Edge. If the Local Loop Type of this line card is not being modified then this attribute may be omitted from the request.  This is applicable to both SBC 1000 and 2000.

CardTwoLocalLoopType	Yes	Yes	isdn_tip:LOCAL_LOOP_LENGTH		<p>Identifies the FXS line card in the second slot of SBC 2000. If the Local Loop Type of this line card is not being modified then this attribute may be omitted from the request.</p> <div data-bbox="1305 432 1503 625" style="border: 1px solid #ccc; padding: 5px;"> <p> This is applicable only to SBC 2000.</p> </div>
CardThreeLocalLoopType	Yes	Yes	isdn_tip:LOCAL_LOOP_LENGTH		<p>Identifies the FXS line card in the third slot of SBC 1000. If the Local Loop Type of this line card is not being modified then this attribute may be omitted from the request.</p> <div data-bbox="1305 982 1503 1176" style="border: 1px solid #ccc; padding: 5px;"> <p> This is applicable only to SBC 1000.</p> </div>
CardFiveLocalLoopType	Yes	Yes	isdn_tip:LOCAL_LOOP_LENGTH		<p>Identifies the FXS line card in the fifth slot of SBC 1000. If the Local Loop Type of this line card is not being modified then this attribute may be omitted from the request.</p> <div data-bbox="1305 1539 1503 1732" style="border: 1px solid #ccc; padding: 5px;"> <p> This is applicable only to SBC 1000.</p> </div>



Helpful Tip

The POST can contain either only the attributes that are being updated, or the full set of attributes for the resource