

# Managing the SIP to Q.850 Cause Code Table

<b>View SIP to Q.850 Cause Code Table</b>	Select the <b>Telephony &gt; SIP to Q.850 Cause Code Table</b> .
<b>Add a SIP to Q.850 Cause Code Table Entry</b>	Insert a new line in the SIP to Q.850 Cause Code Table screen, then double-click the line to present the <b>Edit SIP to Q.850 Cause Code Table</b> dialog box.
<b>Modify SIP to Q.850 Cause Code Table Entries</b>	Double-click on table line in the SIP to Q.850 Cause Code Table screen, to present the <b>Edit SIP to Q.850 Cause Code Table</b> dialog box.

**Editing SIP to Q.850 Cause Codes Dialog**

**Edit SIP to Q.850 Cause Code entry # 1**

SIP Response Code: 503 - Service Unavailable

Q.850 Cause Code: 6 - channel unacceptable

OK

Cancel

Field	Description
<b>SIP Response Code</b>	Select a SIP response code from the drop down list.
<b>Q.850 Cause code</b>	Select the Q.850 Cause code to map to the SIP Response code selected above.